

HYT Hytera 海能達 HYT-S31

外觀線條簡潔 小巧機身 機身紮實 免牌照機 貼心語音 長效續航 內置喇叭 支援手機 apps 0.5-3W



接收状态



发送状态



电量



多种佩戴方式

产品配件

● 标配 ● 选配



●
可拆卸皮带夹



●
吊绳



●
短天线



General

Model HYT-S31/HYT-S31 LF
Frequency Range 400-470MHz (Main Unit)
Channel Capacity 48
Zone Capacity 3
Channel Spacing 12.5kHz/20kHz/25kHz
Operating Voltage 3.8V (rated)
Battery 2200mAh Li-Polymer
Battery Life(5/5/90 Duty Cycle,High TX Power) 15 hrs (3W) / 22 hrs (1W)
Frequency Stability ± 2 ppm
Antenna Impedance 50 Ω
Dimensions(H×W×D) mm 108*53*20mm (without antenna)
Weight 145g (With belt clip);135g (Without belt clip)

Transmitter

RF Power Output 1W/3W (low/high)
FM Modulation 11K0F3E@12.5kHz
14K0F3E@20kHz 16K0F3E@25kHz
Conducted/Radiated Emission -36dBm < 1GHz ; -30dBm > 1GHz
Modulation Limiting ± 2.5 kHz@12.5 kHz;
 ± 4.0 kHz@20 kHz;
 ± 5.0 kHz@25 kHz

FM Hum&Noise

40 dB@12.5 kHz;
43 dB@20 kHz;
45 dB@25 kHz
Adjacent Channel Power 60 dB@12.5 kHz;70 dB@20/25 kHz
Audio Distortion $\leq 3\%$